

SOYBEAN - FIRE ANTS (SUPPRESSION: AT-PLANT)

General Information

GENERAL INFORMATION

SMARTBOX INFORMATION

The SmartBox system should be properly calibrated by a person familiar with operation of the system to assure an accurate application rate of Lorsban 15G. Lorsban 15G must be applied with the SmartBox system. Please refer to the SmartBox operator's manual for detailed information on system operation and calibration procedures. Do not attempt to open or tamper with the SmartBox container. Do not attempt to repair the SmartBox container. If repairs are necessary, contact your local AMVAC sales representative or the manufacturer of the SmartBox system.

Refer to the label for the Application Rates/1000 Ft of Row and Equivalent/Acre at Different Row Spacings.

Limitations, Restrictions, and Exceptions

SOYBEAN

At Plant and Postplant Treatments: Apply as a T-band in a 4 to 10 inch band over the open seed furrow in front of the press wheel and incorporate into the top 1/2 to 1-inch of soil using suitable equipment. For postplant treatment, apply the granules in a 4 to 10 inch band over the row and incorporate into the top 1/2 to 1 inch of soil using a suitable cultivator. Apply Lorsban 15G with equipment that will provide uniform distribution of the granules over the row.

Specific Use Precautions:

- Do not apply as an in-furrow treatment to soybeans.

Specific Use Restrictions:

- Do not make more than 1 application of Lorsban 15G per season or apply more than 3 applications of other products containing chlorpyrifos.
- The maximum single application rate is 1.2 oz active chlorpyrifos per 1000 feet of row.
- Do not make a foliar application of Lorsban 4E or other product containing chlorpyrifos within 10 days of an at-plant application of Lorsban 15G.

Method

[Band](#)

Pre-Harvest Interval

7 days

Rates

[field_rates 0](#)

-

Restricted Entry Interval

24 hours

Exception: If the product is soil-injected or soil-incorporated, the Worker Protection Standard, under certain circumstances, allows workers to enter the treated area if there will be no contact with anything that has been treated.

Timings

[At-Plant](#)